



## Smart 1-10V Converter

- Compact BLE to 1-10V converter for use in OPple Smart Lighting System
- Integrate any brand of 1-10V luminaire into the OPple Smart Lighting System
- Full control of one or more 1-10V luminaires with Smart Switch or Smart App
- Compatible with OPple BLE2 Smart Sensors & OPple BLE2 Smart Switch
- Very easy to set up with the OPple Smart Lighting App, or Smart Connect Box through the web user interface
- Including built-in energy meter, to read out in the app or web user interface
- Complete wireless communication via future-proof, standardized Bluetooth® Low Energy (BLE) SIG Mesh protocol



## Specifications

Item Code	Item Description
821017003000	LEDsmart-BLE2-10V-Converter

Technical Specifications	
IP-class	IP20
Protection	II
Finishing	White RAL9003
Communication	Opple Bluetooth® Low Energy SIG Mesh (BLE2)
Dimming method	1-10V

Electrical Supply	
Nominal voltage	220-240 V AC
Frequency	50 Hz
Connection cable	0.75mm <sup>2</sup>
Cable Length	12 cm



Mechanical Properties	
Material housing	PC

Ambient conditions	
Application Temperature	+25°C
Operating Temperature	-20~+45°C

## Dimensional drawing (mm)

